

## LED Touch Sensor Cabinet lamp--Dimmable

### Product Photo



- 1 The power light is on and the lamp is turned off, the first shorter touch ,the lamp is half-bright (brightness50%)
- 2 Short touch again under the light of the state, the lamp off. Longer touch up regulation of light to increase the brightness for the first time under the lighting station, until the brightest;
- 3 Long touch dimmer again after a long touch dimmer, with the last light in the opposite direction dimmer, down regulation of light to decrease the brightness, until the darkest.
- 4 Released during the dimmable process or stopped the dimmable action, the lamp will keep the current brightness.
- 5 After adjusting the brightness, a short touch, the lamp is off; touch the light again, the lamp enters the brightness of the shutdown.

### Temperature Characteristics

25°C Ambient Temperature

Temperature operating -20~+40°C

Storage: -40~+85°C

Humidity Operating: 10%-80%

Storage: 10%-80%

### Technical Parameters

Model No.	Power (W)	Switch types	Body Material	LED Type	LED Qty (PCS)	CCT (K)	Lumens (lm)	CRI (Ra)	Product size (mm)
OLM.SZAF.D.BN.3W-300	3W	touch-sensitive	Aluminum	2835	30	4000-4500	220±10%	80	300*25*9mm
OLM.SZAF.D.BN.5W-500	5W	touch-sensitive	Aluminum	2835	54	4000-4500	380±10%	80	500*25*9mm

CCT Range: WW: 2700-3200K , NW: 4000-4500K , PW: 6000-6500K

**Productions applications:**

The Kitchen, wardrobe, Wine cellar, jewelry cabinet



橱柜



衣柜



酒柜



珠宝柜





### Installation

1. Using two mounting clips with screws on the installation position, and the two mounting clips are in the same level.
2. Put the cabinet lamp into the mounting clips.
3. Connect the power cord to the power supply.



### Blister package (1psc) accessories:

Items	Cabinets lamp	Adapter	Branch box	1M connector	1.5M input DC connectors	Install mounting clips	Screws
quantity(pcs)	1	1	1	1	1	2	4
No.	①	②	③	④	⑤	⑥	⑦

# Instructions.

